


# Speed 9

ORIGINALITY DESIGN SMART - AND BEAUTIFUL

.....



## QUICK GUIDE



# What's in the box

Please consult this checklist for all parts.



Speed 9



Power adapter



USB cable



Bracket




Screws



Pin




Manual




Power	DC 5V±10%
Status light	<ul style="list-style-type: none"><li>• Red light solids on: the camera network is abnormal</li><li>• Blinking red light: awaiting WiFi connection (faster blinking)</li><li>• Blue light solids on: camera running correctly</li><li>• Blinking blue light: currently connecting (faster blinking)</li></ul>
Microphone	Captures sound for your video
SD card slot	Supports local SD Card storage (Max.128G)
Reset	Press and hold for 5 seconds with pin to reset the camera (if you have modified settings, they will return to factory defaults)
Call	Receive the answer after pressing the button

- 1 Use the included mounting bracket to fix the camera to a clean surface.



- 2 Or, put the camera on a flat surface.





## Download

Smart Life is available for both iOS and Android OS. Search the name 'Smart Life' in App Store or Android Market, or scan the QR-Code to download the App.

Support



iOS



Android



Download App(iOS&Android)

## Set up router

The router supports the 2.4GHz WiFi (doesn't support the 5GHz), and is connected to the WiFi network. Please set the parameters of the router before connecting the WiFi network, and record the SSID and password of your WiFi.



Please keep network available



2.4GHz




5GHz



## Registration process

- Step 1** Open the Smart Life App, click "Register", read the "Privacy Policy" and click "Agree" .



Update date: 2018.4  
Come into force date: 2018.5

So you have purchased our Smart LifeSmart device hardware and are starting to use the Smart LifeSmart device software and all its functionalities! Any information you share with us (e.g. for creating a Smart Life Account) will help us to provide you with services related to Smart LifeSmart device and to improve them to make them even better. We explain here our ways of collecting and using information, and how we protect your privacy. In this privacy policy, "personal data" means information that can be used to identify an individual, either from that information alone, or from that information and other information we have access to about that individual. We collect both personal and non-personal data to enable and facilitate the best user experience possible.

**What information is collected and how do we use it?**

Disagree

**Agree**

- Step 2** Input a legal and valid Mobile number or Email address and click "Continue". Input Verification Code, then log in the app.

### Register

Canada +1 >  
Mobile number/Email

Continue



☒ I agree with Service Agreement and Privacy Policy

### Verification Code



Verification code has been sent to: admin@gmail.com,  
Resend (56s)

# QR Code Configuration

- 1 Open the Smart Life App, click "Create family", and you can customize the Family name and related settings .




- 2 Continue to click "Security & Sensor" >> "Smart Camera", and then choose "Add Device" or "+", ready to add camera.



- 3 In "Add Device" this interface, continue to click "next step", and then you should input your WiFi's passwords.

## Add Device

Power the device on and make sure the indicator is flashing quickly or a prompt tone is heard



Help

next step

## Enter Wi-Fi Password

Only support 2.4GHz Wi-Fi network



### Note:

- 1) Camera only supports 2.4GHz WiFi network.
- 2) The number of bits in the ssid and passwords of the router should not exceed 24 digits.

- 4 In this interface, you should scan the QR code in your phone with the camera, when the camera comes out "dong dong dong". And you can complete the configuration about 30s.

## Scan with the camera

When you tap CONTINUE, the mobile phone displays a QR code. Hold the camera 15 to 20 cm in front of the mobile phone for the camera to scan the QR code.



15~20cm



Heard nothing at all

Continue

Heard the beep

- 5 When connecting, you should make sure your router, mobile, and camera are as close as possible. When camera added successfully, click "✓" you could also DIY the camera's name.



## Connecting

Make sure your router, mobile, and device are as close as possible





- ✓ Device found
- ✓ Register device to the smart cloud
- ✓ Initializing device

## Device added successfully



In "Smart Camera" interface,click "",you can set the camera common functions.



Screenshot



Speak



Record

Q: The device cannot be previewed properly?

A: Check whether the network is normal, you can place the camera close to the router, and if not, it is recommended to reset the device and add it again.

Q: Why is it still in the list of devices after resetting?

A: The reset device only resets the network configuration of the camera, but cannot change the configuration on the App, remove the camera, and must be deleted by the App.

Q: How to cut the camera network to another router?

A: First remove and reset the device on the App and then configure the device again by the App.

Q: Why doesn't the device identify the SD card?

A: It is recommended to plug in SD card after power cut. Confirm whether the SD card is normally available and the format is FAT32. And the TF card can't be identified when the internet environment is not good.

Q: Why I can't get the notifications with my cell phone App?

A: Please confirm that the App has been running on the phone, and the relevant reminder function has been opened; Message notification and authority confirmation in the mobile phone system have been opened.



## Pan/Tilt

Rotate your camera by sliding on your smartphone, providing you with 360 degrees of vision.

## Video flip

Flip your video stream up or down for maximum flexibility.

## Motion detection

Built-in motion sensors detect movement, and the camera will send you push notifications and app alerts.

## Record


Support 24H continuous recording with high capacity SD storage or Cloud storage.

## One-Touch Call

Hear your baby's call anytime, anywhere.

## Day & Night

Never miss a moment, even in complete darkness, with powerful night-vision technology.



Daytime



Night